

# ICT Training Guide Version2

Tom Cannon, David Hart, Chris Brett & Ece Turgay Brett

Chapter       .Page         I.0       The PM3 Monitor         .1       Introduction to the PM3         .2       Getting Started         .3       Operation         .4       Workouts		
The PM3 Monitor		
Getting Started	.5	
Operation	.6	
The Information Section	10	
PM3 Menu Structure	12	
	The PM3 Monitor         Introduction to the PM3         Getting Started         Operation	

## 2.0 The Log Card

2.1	Setting up the LogCard & Common LogCard Tasks	14
2.2	Installing the PM3 LogCard Transfer Utility from the CD	16
2.3	Downloading the LogCard Transfer Utility from the Internet	19
2.4	Downloading Data from the LogCard Using the PM3 LogCard Transfer Utility	
2.5	How to Erase a LogCard	
2.6	What to do if the PM3 Monitor will not Communicate with the PC	
2.7	Creating a Graph of Split Time Vs Distance Rowed from the LogCard Data	
2.8	Downloading the Concept 2 Rowing Log	
2.9	Installing the Concept 2 Rowing Log	34
2.10	Using the Concept 2 Rowing Log	
2.11	Deleting Files from the LogCard Using the Concept 2 Rowing Log	41

## 3.0 The Personal Training Log

3.1	The Personal Training Log
3.2	Current Season
3.3	History
3.4	Challenges
3.5	Ranked Workouts
	Profile
3.7	Teams
	Rankings
3.9	Logout

Chapt	ter	Page
4.0 Ve	enue Racing	
4.1	Downloading the Venue Racing Software	
4.2	Installing the Venue Racing Software	
4.3	Using the Race Venue Application	51
4.4	Use in Schools	
4.5	How to set up a New Race in the Race Venue System Software	
4.6	Opening Saved Races	
4.7	How to Change the Race Setup	
4.8	How to Change Race Options	
4.9	Showing More Race Information	61
4.10	Changing the Race Display Scale	62
4.11	How to Get Help	62
4.12	Downloading Support Documentation for PM3 Venue Racing.	


# 5.0. Updating the Software on the PM3

5.1	Downloading the Firmware Updater	.65
5.2	Installing the Firmware Updater	.66
5.3	Using the Firmware Software	.67

# The Performance Monitor 3 (PM3)

#### 1.1. Introduction to the PM3

Battery compartment under back panel



The PM3 is designed to be menu driven and self-explanatory. We encourage you to spend a little time pushing buttons and following the menus. If you press the wrong button, just use the "MENU BACK" button to return to the previous menu. If you dislike pushing buttons, just pull on the handle and the PM3 will automatically start displaying and storing your results. For additional information select [Information] from the main menu.

#### **Bottom View**



Flywheel sensor cable must be connected here for the PM3 to operate. The Model D sensor will also supply power to the PM3 while you are rowing. The PM3 can be set to operate with either the Model D or Model C. They are not interchangable.

Port for the optional heart rate receiver.

USB Port for connecting to a personal computer. See www.concept2.com/pm3 for current information on PC functions.

#### 1.2. Getting Started

- The PM3 turns on when you press the "MENU BACK" button, take a stroke, or insert a LogCard.
- The PM3 turns off automatically after four minutes of inactivity.
- The first time you turn on the PM3, you will be prompted to set the language, date and time.

**IMPORTANT**: Setting the date will allow your results to be stored correctly.

#### 1.3 Operation



Lets you select one of four units for your results: meters (or time), time/500m, watts, and calories. This button is active in rowing displays, result screens, and when setting PaceBoat.

Lets you select one of five rowing displays:

All Data > Force Curve > PaceBoat > Bar Chart> Large Print.

This button is only active from the rowing displays

Returns you to the previous menu. From rowing displays, "MENU/BACK" ends the workout and returns you to the main menu.

#### 1.4 Workouts

#### **Pre-Set Workouts**

There are three kinds of pre-set workouts in the PM3: [Standard List], [Custom List] and [ReRow]. If you have a LogCard, you can also access [Favourite] workouts.

From Main Menu: [Select Workout]> [Standard List]> Select from the standard list of workouts that includes: 2,000m, 5,000m, 10,000m, 30 minutes and an interval workout of 500m/1:00. When you select a workout, it will automatically be set up on the rowing screen. The workout begins when you start to row.

From Main Menu: [Select Workout]> [Custom List]> Select from workouts that have previously been set up and stored. The PM3 comes with a list of custom workouts, but if you have a LogCard you can replace them with your own. With your LogCard inserted select [Set Workout]> [New Workout]>. When you have finished setting up the workout you will be asked if you wish to save the set-up to your Favourites. Later, you can use [More Options]> [Edit Custom List]> to copy one or more workouts from the LogCard to the PM3 memory.

From Main Menu: [Select Workout]> [ReRow]> Then select the type of workout you wish to ReRow. You will then be able to view a list of previous workouts. Select the workout you wish to ReRow. That workout will automatically be set up on the rowing screen and your previous performance will be used to drive the PaceBoat.

Favourites: (Only available with LogCard inserted) [Select Workout]> [Favourites]> Select a workout from the list of favourites previously programmed using [Set Workout]> [New Workout]> (see below).

#### **Programming Workouts**

The PM3 allows you to program your own specific workouts.

From Main Menu: [Select Workout]> [New Workout]> Then select the type of workout from: [Single Distance], [Single Time], [Intervals: Distance], [Intervals: Time] or [Intervals: Variable]. Enter the information needed to set up the desired workout, using the five side buttons next to the [ $\rightarrow$ ], [+], [-], [ $\triangleleft$ ] and [ $\checkmark$ ]symbols. When you have finished with the set-up, select [ $\checkmark$ ] for done. The PM3 will then be ready to start the workout as soon as you start to row.

When programming [Single Distance] or [Single Time] workouts – The PM3 allows you to program the duration of the workout, the split length for memory storage (see below) and the optional PaceBoat speed.

When programming [Interval Distance] or [Interval Time] workouts - The PM3 allows you to program the duration of each interval, the rest period in between each interval and the optional PaceBoat speed.

**NOTE:** For any interval workout the first interval starts when you begin to row. All other intervals start as soon as the rest period is finished.

When programming [Intervals: Variable] The PM3 allows you to set a different distance or time and rest period for each interval up to a total of 30 intervals.

#### Splits


Single piece workouts are split into segments called "splits" for storage and analysis. The PM3 will default to five segments or splits per piece. You can change this to a desired split time or distance. Note that a maximum of 30 splits are allowed per workout, and the minimum split size is 20 seconds for time or 100 metres for distance. There are no splits for interval workouts. Note that more splits require more storage space on the LogCard and if you choose to store more splits per workout, the LogCard will store fewer workouts.

#### 1.5 Drag Factor

The Drag Factor is an accurate measurement of the Air Resistance created by the Fan inside the Fan Cage of the Concept 2 Rower. The Drag Factor can be adjusted by moving the damper lever on the side of the flywheel. The Drag Factor can be viewed from the More Options menu. Select [More Options]> [Display Drag Factor]> then row normally to display the current Drag Factor on the PM3 Monitor.

To increase the drag factor raise the damper lever and to decrease the Drag Factor Lower the Damper Lever. This will alter the feel of the stroke. High numbers feel slow and heavy, lower numbers feel quicker and lighter and more like a racing boat. It is best to use a Drag Factor between 100 and 140. This is usually a damper number between 2 and 5. Use a Drag Factor that feels most comfortable to you and gives you the best result for the workout.

The damper lever setting required to achieve a certain Drag Factor will vary from one machine to another due to elevation, manufacturing tolerances and accumulated dust inside the flywheel cover.



2. To find out more about Drag Factor use the PM3 Information function. Select [Information]> [Drag Factor]>

#### 1.6. Display Options

The PM3 has 5 Graphic Display Options which can be selected using the 5 side buttons or by repeated pressing of the "Change Display" button to cycle through the different choices. The options are as follows:

#### 1.6.1 Large Print

Provides basic data in a large, easy-to-read format.

Time - How long you've been rowing or still have to row.

**Stroke Rate** - Measured in strokes per minute (s/m), updated every stroke.

**Stroke Output** - How hard you pulled on the last stroke. Displayed in a choice of three units: pace/500m, calories/hour and watts.

**Total Output** - Cumulative output since you started rowing. Displayed in a choice of four units: average pace, metres, calories and average watts.


**Heart Rate** - If a heart rate interface is attached to the Rower and you are wearing a chestbelt transmitter, this display will show your heart rate in beats per minute.


Note: The same basic data which appears in Large Print also appears in a smaller format in the top half of the screen of the other four displays.

#### 1.6.2 All Data

Additional numeric information is displayed. The top line in the bottom half of the screen shows your accumulated score in time, metres or average time/500m depending on the units you have selected. During a Just Row, Single Distance or Single Time workout, the middle line shows your accumulating or average result for the current split. During a work interval the current interval number is displayed.

The bottom line is a projected score for your workout if you continue rowing at your current pace. During a Just Row workout your projected metres for a 30 minute row will be displayed. During a rest interval the total workout metres are displayed, including rest metres.





#### 1.6.3 Force Curve

The Force Curve display option provides a graph of force against time which shows how you apply your force during the drive phase of each stroke.


Good technique will be illustrated by a smooth curve which builds to a peak before decaying back to zero at the finish.

Any distortion to the smooth line of the curve can be attributed to a fault in technique.

Some of the most common faults are:

Driving the legs down too hard, causing the force time curve to rise sharply but then start to decrease before climbing again following the normal path. This type of curve is most commonly seen amongst women and can be attributed to an imbalance between a weak upper body compared to much stronger legs.

The second most common fault is a step up or plateau just before the finish. This is more common amongst male rowers and is caused by not using the legs properly at the beginning of the drive and then tugging the finish into the body at the end of the stroke.




#### 1.6.4 PaceBoat

The PaceBoat display option allows you to row with a virtual competitor.

To set a PaceBoat follow [Set Workout]> [New Workout]> and program the speed of the PaceBoat as part of your workout.

To ReRow against a previous performance follow [Set Workout]> [ReRow]>

If no pace is set the PaceBoat will simply mirror your speed. ReRow uses the selected split results for the speed of the Pace Boat.




#### 1.6.5 Bar Chart

The Bar Chart display option creates a graphic display of your last 50 strokes.

As you vary the intensity of your workout the range of the display will change to keep your most recent strokes in view.


If a heart rate interface is attached to the rower and you are wearing a chestbelt transmitter, your heart rate will automatically be plotted every 10 seconds instead.



#### 1.7. The Information Section

As mentioned earlier the 'Information' section contains information on how to use the Concept 2 rowing machine including sections on [Drag Factor](see 1.5.), the use of the PM3 [PM3 Details] and [How to Row] which includes instruction on basic rowing technique.

To view the Information section simply select [Information]> from the initial start up Menu.



#### 1.8. Batteries and Power Generation

The PM3 uses two alkaline D-cell or IEC CR20 batteries. It also self-generates if you are using a Model D Indoor Rower or a Model C with retrofit. Depending on the speed of rowing, the PM3 will generate some or all of the power needed for its operation. This will extend the life of your batteries.

Batteries are needed to maintain date, time, language, Custom List and Memory.

Batteries can be removed for five minutes without loss of this information, if the PM3 is turned off before the batteries are removed.

When your batteries are low, the following warning will display when you turn on the PM3: "Replace batteries soon."

When your batteries are very low, you will be warned "Batteries too low for normal operation". If you keep the batteries in, and if you have the self-generation feature and start rowing fast enough, you will automatically go into Just Row mode. The display will work, but you will not be able to set up workouts, and your workout data will not be saved.

To change batteries, first allow the PM3 to power down so as not to lose any saved data. Then remove the cover, carefully pry the batteries out and replace within five minutes.

To view the current level of battery charge remaining select [More Options]>[Utilities]>[Battery]>

#### **Battery Life Expectancy**

- For Model B or C without retrofit: 300-400 hours.
- For Model D, or C with retrofit, normal use: almost the shelf life of the battery.

#### **Additional Notes**

#### Care of PM3

Clean with damp cloth only. Do not apply liquids directly to the PM3.

#### Formulae

The following formulas are used to equate the units of measure:

#### Watts = 2.80/(sec/meter)<sup>3</sup>

Cal/hr = Kcal/hr = (watts) x (4) x (0.8604) + 300

# PM3 Menu Structure

Just Row......Up to 50,000m without pressing any buttons. Results saved if longer than one minute. Splits default to 5 minutes; after 35 minutes, splits default to 10 minutes; etc. Press MENU BACK when finished to ensure that your results are saved. Select Workout Standard List .....Includes five pre-set workouts, not changeable. Custom List.....Includes five workouts, can be replaced with workouts from a LogCard. Limit of 30 variable intervals - total. ReRow ......Enables user to select a previous result to drive PaceBoat. New Workout ......Enables user to design a workout in any of the following formats. Single Distance ......100m to 50,000m. Single Time......0:20 to 9:59:59; distance cannot exceed 50,000m. Intervals: Distance ......Constant work from 100m to 9999m; constant rest time from 0 to 9:55; up to 30 intervals. Intervals: Time ......Constant work from 0:20 to 59:59; constant rest time from 0 to 9:55; up to 30 intervals. Intervals: Variable ......Combination of distance and time from 100m to 999.999m or 0:20 to 99:59:59: rest time from 0 to 9:55; up to 30 pre-set intervals. Favourites ......Five workouts per LogCard user. Limit of 30 variable intervals total/user. Memory......If no LogCard present, lists about 10 most recent workout results by date; oldest are automatically deleted. OR LogCard......Stores about 300 workouts, each user's five favorite workouts, preferred language, last used units and display type. It is a good idea to keep backup records of important result data. Summary.....Lists users total and average results recorded on LogCard. Monthly Totals ......Shows a table of monthly workout totals. List by Date.....Enables you to look up workout results by date. List by Type.....Enables you to look up workout results by type. - LogCard Utilities Add User.....Adds up to five users per LogCard. Edit User ......Edits name and "lifetime meters". Delete User ......Deletes name and results. Delete Workout ......Deletes results from LogCard. Copy Workout .....Copies a workout from PM3 memory to LogCard. **Information..**Go to this menu for additional PM3 information. This menu selection is an on-board manual. We suggest that you read it. **Overview** Using the Monitor .....Describes the PM3 buttons, rowing displays, workouts and LogCard. How to Row ......Gives a brief "rowing lesson" with technique animation. Drag Factor/Damper .......Is a measure of the fan load. The PM3 self calibrates by recalculating the drag factor every stroke so you get a true measure of your effort regardless of the damper setting or changing conditions. Replacing the Battery......Use two alkaline D-cell or IEC CR20 batteries. To prevent loss of information, be sure the PM3 is turned off before removing old batteries, and install the new batteries within five minutes **More Options** Display Drag Factor ......Allows the user to view and set the drag factor before rowing. Utilities Set Date and Time.....Is important for result storage. Set Language .......Sets preferred language. Defaults to preference set on LogCard or last language set on PM3. LCD-contrast......Adjusts the LCD lighter or darker. Battery ......Shows % battery life remaining. Product ID .....Shows product identification information. Edit Custom List.....Copies workout from Favorites to Custom List if LogCard is present.

# The LogCard

### 2.1. Setting up the LogCard and Common LogCard Tasks

The LogCard allows you to:

- Store hundreds of detailed workout results.
- Edit your lifetime metres to include workouts not stored on the LogCard.
- Save your favourite workout settings.
- Race against a previous workout.
- Remember your preferred language, display and units.
- Add up to five users per card.

Your LogCard will automatically be formatted the first time you insert it in the PM3. You will then be instructed to:

Add New User - Set your user name using up to six letters.

If you would like to carry forward your previous lifetime metres to this LogCard, From Main Menu: select [LogCard]> [LogCard Utilities]> [Edit LogCard]

Each LogCard can serve up to five users, but heavy users will probably want to have their own card. The LogCard will hold hundreds of workout results and you will be warned when it is filled.

#### To add additional users to your card:

From Main Menu: select [LogCard]> [LogCard Utilities]> [Add User]

#### **To delete a user from your card**: *From Main Menu: select [LogCard]> [LogCard Utilities]> [Delete User]*

To make a correction to your LogCard or User name:

From Main Menu: select [LogCard]> [LogCard Utilities]> [Edit LogCard]

#### To delete a workout from the LogCard:

From Main Menu: select [LogCard]> [LogCard Utilities]> [Delete Workout]

#### **To copy a workout from LogCard to PM3 Custom Workouts**: From Main Menu: select [LogCard]> [LogCard Utilities]> [Copy Workout]

Your total workout results and the split or interval data are stored automatically in the PM3 Memory and on the LogCard. Also displayed are the average stroke rates and the ending heart rates (if the heart rate option is used). When the PM3 memory is full, the oldest result will be deleted. The LogCard will hold hundreds of workout results and you will be warned when it is full.

#### If no LogCard is installed

From Main Menu: select [Memory] to view a chronological list of the last workouts that fit into the memory. Use the cursor buttons to select the workout you wish to view. The memory stores data for each split or interval of your workout.

#### If a LogCard is installed

From Main Menu: select [LogCard]. Or, from the LogCard User screen, select [LogCard Menu].

You will then select how you wish to view your log information.

A one page summary of your log.

A history of your monthly totals.

A list of your workouts by date. Use the cursor buttons to select the workout you wish to view in detail. The LogCard stores data for each split or interval of your workout.

A list of your workouts by workout type. Use the cursor buttons to select the workout you wish to view in detail.

As with all electronic storage media, we encourage you to make frequent backups of your LogCard data, either by transferring it to a PC or keeping written documentation of key data such as Lifetime Total Metres.

#### How do I update my lifetime meters on my LogCard?

The PM3 LogCard keeps track of your lifetime meters for you. By default, this will be the total meters for your user on the LogCard. If you would like to update this value to include actual previous lifetime meters (those not recorded on the LogCard),

From the PM3 Main Menu: select [LogCard]> [LogCard Utilities]> [Edit User]

Update the lifetime meters displayed by using the buttons next to the  $[\bullet]$ , [+], [-],  $[\bullet]$  and  $[\checkmark]$  symbols to navigate through the digits and to increase/decrease the values.

Click the  $[\checkmark]$  button to save the new value.

#### **Changing Users**

To switch between users on a shared LogCard, remove the card, Goodbye will be displayed on the PM3, and then reinsert it to log in as another user. Select the desired user from the list.

# Is there a way to load the data from the PM3 and the LogCard into my Concept 2 Online Ranking Logbook or do I need to log each workout individually?

At the present time, you will need to manually load your results into the Concept 2 Online Ranking Logbook. As an option, you might consider purchasing RowPro from www.digitalrowing.com which provides this feature.


#### My PC is not near my PM3/Indoor Rower. What can I do in order to use the LogCard Utility?

The PM3 can easily be removed from the rower and taken to the location of your PC. To remove the PM3 from the rower, unplug the wire coming from the flywheel pick-up, and remove the bolt that attaches the PM3 to the monitor arm.


**Note:** If you do this regularly, you may want to obtain a wing nut from your local hardware store or you can call Concept 2 and order PN 124.

#### 2.2. Installing the PM3 LogCard Transfer Utility from the CD

Insert the CD titled "PC software for your PM3" that came with your PM3 or Model D. This will automatically open the Concept 2: PC Software Suite (if this does not open automatically go to the start menu, select my computer and then select the CD drive). Once opened the Concept 2: PC Software Suite should look like this:



Click on the C2 button next to the PM3 LogCard Transfer Utility text to install the PM3 LogCard Transfer Utility. After a short delay the following dialogue box will be displayed.



Click Next >

This will take you to the Licence Agreement. Please read this and then check I accept and then click **Next>** to proceed.



Then the following screen will be displayed. Complete your username and organisation details then click **Next>**.

🖗 PM3 LogCard Transfer Utility - InstallShield Wizard	×
Customer Information	Co
Please enter your information.	- Ch
User Name I	
I	
Organization	
Install this application for :	
Anyone who uses this computer (all users)	
Only for me ( )	
InstallChield	
<back next=""></back>	Cancel

The Software will load by default into the Program Files folder on the C: Drive. It will create a folder called Concept 2 if one does not already exist. If you would like to change the location of this program click change and select the folder where you would like it. When you have chosen the desired program location click **Next>**.

i₿ PM3 Lo	gCard Transfer Utility - InstallShield Wizard 🛛 🕅
Contraction of the local division of the loc	ion Falder at to install to this falder, or click Change to install to a different falder. 📿
-	Instal PM3 LogCard Transfer Utility to: C: [Program Piles]Concept2[LogCard Transfer Utility], Change
Initalithiadd-	< Back Next > Cancel

You will then be shown a screen showing where the programme will be saved. Select Install and the programme will be installed.

stalling	gCard Transfer Utility - InstallShield Wizard 1943 LogCard Transfer Utility granfeatures you edected are being installed.	Q
得	Please wait while the InstallSheld Wizard installs PM3 LogCard Transfer Utility . This may take several ninutes. Status	
	(*****	
althed -		

Once the installation is complete the following screen will be displayed.


🖉 PM3 LogCard Transfer U	tility - InstallShield Wizard 🛛 🕅
	InstallShield Wizard Completed
	The InstallShield Waard has successfully installed PM3 LogCard Transfer Ublity - Click Pinish to exit the waard.
	Show the readine file
	< Back Prink Cancel

If you want to view the readme file check the appropriate box. This is a text **(.txt)** file which can be viewed using Notepad or Wordpad. Click on Finish and the LogCard Transfer Utility installation will be complete.

#### 2.3. Downloading the LogCard Transfer Utility from the Internet

The LogCard Transfer Utility can also be downloaded from the internet. This method will install the latest version of the software. It also makes it possible for users who have not got the Concept2 PC Software for your PC CD to install the software. To download from the internet open up Internet Explorer (Start> Internet Explorer). Then type the following address: **www.concept2.com/05/rower/service/pm3software.asp**. Scroll down to the LogCard Utility section and click on the highlighted LogCard Utility link. This then leads to a page like the one below:





Scroll down to the Save or Run PM3 LogCard Utility Setup section as shown (opposite / below):


To install immediately click Run. When the download is complete click Run to start the installation. This will open the Installation Wizard. Follow the instructions to complete the installation.

To install at a later time click Save and select a download location for the installation file. Once the file has been downloaded, the software can be installed at any time by navigating to the download location and double clicking on the installation file. As above this will open the Installation Wizard. Follow the instructions to complete the installation.

### 2.4. Downloading Data from the LogCard Using the PM3 LogCard Transfer Utility

Using the USB cable that comes with the PM3, connect your computer to the MP3 Monitor.

(The connection for the USB cable can be found at the bottom of the monitor).



Flywheel sensor cable must be connected here for the PM3 to operate. The Model D sensor will also supply power to the PM3 while you are rowing. The PM3 can be set to operate with either the Model D or Model C. They are not interchangable.

USB Port for connecting to a personal computer. See www.concept2.com/pm3 for current information on PC functions.

After downloading and installing the PM3 LogCard Utility Version 3.0.2, the first page which appears should be similar to the one opposite.

Within this page you can transfer data, change users, and change information on the LogCard.

To use all of the features you may have to download a new version of the PM3 Update Utility from **www.concept2.com** 



#### TRANSFER DATA

#### Transfer LogCard data to Spreadsheet

To transfer data from the LogCard to a spreadsheet, click upon **'Transfer LogCard data to Spreadsheet'** in the Transfer Data option with in the initial screen. A screen similar to the one opposite should appear.

After selecting an appropriate file name then click **OK**. There is the option of clicking upon automatically open file in Excel, which means that the file will open up in excel.

The LogCard will then be read and the data will be saved in a format which can be opened up in a spreadsheet. You will then be returned to the initial launch page.



#### Transfer LogCard data from backup file.

To transfer data from the LogCard from a backup file, click upon **'Transfer LogCard data from backup file'** in the Transfer Data option with in the initial screen. A screen similar to the one opposite should appear.

Change the Backup file and the file where the data will be interpreted to, to a file which is appropriate. There is the option of clicking upon automatically open file in Excel, which means that the file will open up in excel. Then click **OK** 

Then the files will be created and you are returned to the launch page.



#### **MAINTAIN USER**

#### **Erase Workouts**

To erase workouts found on the LogCard click on the **'erase workout'** box within the maintain users section. This should then lead onto a page similar to the one opposite.



At this page select the appropriate user who appears on the drop down list. They will be the users whom currently use the card. Also select whether you want all of the user's workout data deleted or some before a specific date which can be chosen, by clicking on the appropriate box. The click on **OK** to continue.

The LogCard will then be read, and a final confirmation box will appear. Click either YES to continue or NO to stop the process.

Then the LogCard will delete the specific workout data and returns you to the initial opening page.



#### Move a User

Move user and data to a different LogCard

To move user and data to a different LogCard found on the LogCard click on the **'move user and data to a different LogCard'** box within the maintain users section. This should then lead onto a page similar to the one shown opposite.

From this page select the appropriate user from the pull down menu and then click on **OK** to continue.

You must have a formatted blank LogCard for this process to happen otherwise all of your data will be lost.



The LogCard is then read, and a final confirmation box will appear. Click either **YES** to continue or **NO** to stop the process. At this stage you must have a blank LogCard ready.

The LogCard is then read and the data is removed. A screen similar to the following one should then appear.

Insert the new blank LogCard and then press **OK**.

The LogCard is then read and written and then you are returned to the initial page on the PM3 LogCard Utility Version 3.

#### **Delete a User**

To delete a user found on the LogCard please delete it manually on the PM3.



#### **MAINTAIN LOGCARD**

#### Save LogCard data to file

To save LogCard data to file click on the **'Save LogCard data to file'** box within the maintain LogCard section. This should then lead onto a page similar to the one shown opposite



You then have the option of changing where the file is save. You can either accept the default on or chose a new file by clicking on Browse and the finding an appropriate file you wish to save it too. The click **OK**.

The LogCard is then read and the data saved. You are then returned to the initial menu page.

B PM3 LogCard Utility To	n 30.7	
CIconcept		
		100
	Save LogCard Data	
92	This will back up your LogCard to a file on your PC	
	2/PM3 LogCard Date/PM3LogCard backup.kb Box	04
		_
	Back	к

#### Restore LogCard data from file

To restore LogCard data from file click on the **'Restore** LogCard data from file' box within the maintain LogCard section. This should then lead onto a page similar to the one shown opposite.

You then have the option of changing where the file is uploaded from. You can either accept the default on or chose a new file by clicking on Browse and the finding an appropriate file you wish to upload. Then click **OK**.

The LogCard will then be overwritten. Click **YES** if you are sure or click **NO** if you do not want this to happen.

The LogCard is then read and the data saved. You are then returned to the intial menu page.



#### **Duplicate entire LogCard**

To duplicate entire LogCard data from file click on the **'Duplicate entire LogCard'** box within the maintain LogCard section. This should then lead onto a page similar to the one shown opposite.

Insert the orginal LogCard which you want to be duplicated and click  $\ensuremath{\textbf{OK}}$  .

The LogCard is then read and a screen similar to the one opposite appears.

Remove the original LogCard and insert a new LogCard. Then click  ${\bf OK}$  to continue



The LogCard is then duplicated. You do have the option to make additional copies of the LogCard by inserting a new LogCard and clicking **OK**. To finish please click **Back**, this will return you to the initial main menu.



#### 2.5 How to erase a LogCard and start over

#### Erase all LogCard data and users

To erase all LogCard data and users click on the **'Erase all** LogCard data and users' box within the maintain LogCard section. This should then lead onto a page similar to the one shown below.

Click **OK** to continue.

A confirmation box then appears. Click **YES** to continue or **NO** to cancel the process.

The date and user are then erased and you return to the initial menu.



#### 2.6. What to do if the PM3 Monitor will not Communicate with the PC

- 1 Ensure that you have saved any workouts to your LogCard.
- 2. Disconnect the USB Cable.
- 3. Ensure that the USB connector in the PM3 is solidly attached. (Sometimes the USB jack becomes physically disconnected from the circuit board due to excessive cable insertion force. If it is loose, please contact Concept 2 to discuss replacement/exchange options.)
- 4. Remove one of the batteries in the PM3.
- 5. Press a button on the keypad and release.
- 6. Leave the battery out for one hour or more.
- 7. Reinstall the batteries and set the language, date, and time.
- 8. Try attaching the PM3 to the PC again. If the PC still cannot talk to the PM3, leave the batteries out overnight and try the preceding steps again using a different USB cable.

# 2.7. Creating a Graph of Split Time Vs Distance Rowed from the LogCard Data

2.7.1 Download the information from the LogCard, as explained in the section Downloading data from your LogCard.

2.7.2 Excel will have opened a spread sheet with your data open. This will look something like this.

								5 83	Del		100.000					
	YOP								(1116)				( in so )			
•	Name of Street, or other	2.1														
ģ	A.			0	t		ō		1	1	×.	L		5	0	ľ
8	ing Dates	Ada .														t
		i lana	244	Tree of C	diam'r ar		life internal	DPM .	Press Press		Address.	1214	Same Late		destated in Califier	72
			_	_		-					_	_		_	_	T
		Aler	12105		A FERRE	21-01	60.0	1						11454	HD	
		Aler	12105		1000					10.021	28		- 682	11543	1.00	
Ū.		A81	10.000		states					10.02.0	506		191	in fast	128	
ŧ.		A81	A185		10001					-883	- 15		- 18	11544		
		Alsi	w105		10001					-053	- 100	27	P08	11546	110	
Ū.		Aller	4105		10000					10.004			554	11.507	112	
0		Ada	4105		10004					10.071	100		105	11143	110	
0		Alter	4788		10001					10107-8			161	21.36/0		
0		Alti	4788		10001					10.074			565	11141	109	
1		Alex	4700		10001					10-018				19.80.3	113	
0		Ale:	1788		ALC: NOT					10.471	388			21-642	110	
ũ		Alex	1700		ALC: NOT					10-17.1			170	21.602	111	
		Am	10.000		A COLOR					12-36.9				21404		
		Ader	1000		A FERRE					(0.47.)	1048			1146.0		
		Aler	10.00		A FERRET					10-512				1140.4		
l		Aler	10.000		1000					1044.4				21 KC II 24 KC II	HO	
		Alex	12105		LOID:										- 10	
		Add	1005							-223			-	-152	114	
		A81	4105		10001									11500	10	
1		Alle	4100		000					10.00				11 504	117	
ţi,		Am	4100		10001					10.04						
l		100	100		- URDAN					10.04.1				11107		<u>.</u>
	1 1 2 1			10.00	·				a. 2740				_	11104		۰.,

2.7.3 Highlight the columns that you would like to create the graph from, i.e. metres rowed against split/500. To highlight two columns that are not next to each other, highlight the one for the x-axis (metres) then press Ctrl on the keyboard and highlight the next column for the y-axis (split 500m). This should look like this:


**Note:** At the top of the Metres Column there is a blank cell highlighted, this is because the Split shown is the average split for the session.

•	P. 18		an span													
×.				5 m		日中に	+ N II	- A - A	- 71b	e de de la	199.24	254	Territor			
	e 19 i	22.0	12.00 3	10.000	5.0	1.111.1	i i	5 8 4	1075 1	13 回。	1.1.1 10		- 14	4		
6	12. 15.	N 10 1			- 11.1	a 25 - 1										
-	41 0		A KUT O													_
		- C	1	- 0-		1	1			54	5	0	- 2	- 0	R .	
			-						-		_			_		
			Terrina					10.0004			Report	PURCHT 1	T-response in the	INFANS -	ter Boyle	
		openational and		Melleri		Read TO	to the	Eagle-t-	1944	Heat Boy				Tan	10,000	
Ω.	- 53	4 10020-1	11年1	000		21	S		_		2144	111	178			
ų.	-83	4 1000					10100.0				COLUMN STATE	116	20			
Ŧ		A 1000-					10.01		X			100	241			
ł		A 1000-					10101.0		- 21		0140.2	118				
ł.		A 0100-					10-00.0				OFFICE	101	- 20			
t		4 000-					10-00.0			10		101	20			
		4 (10)					10-07-3		- 9	10		100				
g.		A COLOR					1000			10		100				
ų.		a dilitica					Here's				019.3	110				
H-		a different					ind i	20	- 5	+0						
н.		a debier					1054	- 26		- 10		- 102	- 9			
÷		4 10000-0					1000			- 14		114	- 194			
÷		4 1000					1007.4		- 7			106				
ł	- 14	4 10000-1					10071		- 9	80		1100	- 10			
ł		4 1000-					10.07.0			10		107	127			
t		4 1000-					1017.0		- 2	80		100	28			
ł	- 64	4 10 20-					1007		- 2	10		108	21			
t.		4 0100-					10-01 8		- 2			100	- 28			
t		14 (0100m					10/07 4		- 21	85		104	281			
t		14 (0100m					1047.2			108	0144.4		25			
t.		4 (000)					10/07 2	106			0114.4	114	28			
a.		a dilitie					10/01 2	0.0	1 12	1.0	0154.4		264			
IT.		a different					10-011	05		5.0	01554	101	267			
t.	- 623	A shiften "					10-34	100	- 8		0150	110	- 3			
e.																
it.																

£0,

2.7.4 Once the two columns have been highlighted press the Graph button

2.7.5 Select the line graph option. This will show you the following screen:




2.7.6 To make sure that your graph will look right press and hold the button that says **"Press and Hold to View Sample"**.

2.7.7 Press "Next >"

2.7.8 This will give you a screen like this:

2.7.9 If your graph looks correct press **"Next >"**. If it is not correct then you will need to adjust the series that the graph is being created from. To do this press the **Series** tab.



This will show you the following screen:

First make the x-axis correct by pressing the **X-axis** button. This will allow you to highlight the cells in the original spreadsheet that you want for the x-axis. In this case the metres cells. This will look like this:


Note that the cells have remained highlighted but the ones that you want for the x-axis have to have the dotted black line around them. Once you are happy that you have selected the correct cells then press "**Return**" on the keyboard.

			MLO		
	H153.8 2041.3 2041.3 2050.2 20	~~~	****		<u>40</u>
Series COLES		- Nonei	Sheeti.t#	454	N
÷	ld Bener	⊻ ¥alues ni	=Sheeti.t\$7	45:\$1\$20	2
Cabag	ory (X) axis labe	elsi 🖡	-Sheet:11\$3\$5i\$3	\$28	ł

'X-Axis' button

NO         N         Statute           1<		P 100 0				2 - 213	1.00		0 B-				•		
Ind         Ind <th>-</th> <th>\$ 1001 B</th> <th>0</th> <th></th> <th></th> <th></th> <th></th> <th>_</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th>	-	\$ 1001 B	0					_							
Instruction         Next         PM         Next First		P		н			- K	L.	- 18	н		- P		- K	
Instruction         Next         PM         Next First		ALC: NO.				10.0 m 10.0				1 m m				and in case of	
0.9 million         36.401         Ball         3         8         0.9 million					Read Votes							Table I	Test.	Mago.	1
0.9 0000         0.96 26         1.6         0.75 3           0.9 0000         0.94 56         0.94 56         0.94 56         9.850           0.9 0000         0.94 56         0.94 550         0.94 550         9.850           0.9 0000         0.94 56         0.94 550         0.94 550         9.850           0.9 0000         0.94 500         0.94 550         0.94 550         9.950         9.4 650           0.9 0000         0.95 560         0.94 550         0.94 550         9.95 560         9.95 560         9.95 560           0.9 0000         0.95 560         9.95 560         9.95 760         9.95 77 850         9.95 780         9.95 7800 <td< td=""><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>10.11</td><td>28</td><td></td><td>-</td><td>1</td></td<>											10.11	28		-	1
O 9 0000         O 9 4         Set         0         14         MESS           C 9 4 0050         C 96 0         7         1         9 3030           C 9 4 0050         C 96 0         92         7         1         9 3030           C 9 4 0050         C 96 0         92         7         1         9 3030           C 9 4 0050         C 96 0         92         1         0         9 3030           C 9 4 0050         D 93         94         9 403         9 40         9 403           C 9 4 0050         D 93         0         9         9 40         9 40         9 40           C 9 4 0050         D 93         0         9         9 40         9 40         9 40           C 9 4 0050         D 93         D 93         0         9         9 40         9 40           C 9 4 0050         D 94         D 94         9 40         9 40         9 40         9 40           C 9 4 0050         D 94         D 94         D 94         0 94         9 40         9 40           C 9 4 0050         D 94         D 94         D 94         0 94         9 40         9 40           C 9 4 0050         D 94         D 94					- 1	No.	- 264	15	+ 101						
P M 4000         E784         PE         P <t< td=""><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>- 8</td><td></td><td>1000</td><td></td><td>- 12</td><td></td><td></td><td></td></t<>								- 8		1000		- 12			
P M 4005         The 300         The 4005											114	- 50			
0 H (600- (1000-))         0 H (100- (1000-))         0 H (100-(100-))         0 H (100-(100-))	OTT IN										- 48	- 54			
0         800.0         0000         800         21         00         800.0           0         0.001.0								- 9			111	- 19			
0 % Maller         D G 7 1         0%         3         44         3645           0 % Maller         D G 7 1         36         3         46         3645           0 % Maller         D G 7 1         36         3         46         3645           0 % Maller         D G 7 1         36         3         46         3645           0 % Maller         D G 7 1         36         3         46         3645           0 % Maller         D G 7 1         36         3         46         3645           0 % Maller         D G 7 1         36         3         46         3645           0 % Maller         D G 7 1         36         2         16         3643           0 % MBD         D G 7 1         36         2         16         3643           0 % MBD         D G 7 1         36         2         16         3643           0 % MBD         D G 7 1         36         2         16         3643           0 % MBD         D G 7 1         36         2         16         3643           0 % MBD         D G 7 7         36         2         16         3643           0 % MBD         D G 7 7 <td< td=""><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>- 3</td><td></td><td></td><td>111</td><td>18</td><td></td><td></td><td></td></td<>								- 3			111	18			
C 9 0000         O 9 1         28         3         10         8560           0 9 0000         005 5         28         3         10         8560           0 9 0000         005 5         28         3         10         8560           0 9 0000         005 5         28         3         10         8560           0 9 0000         005 5         28         3         10         8560           0 9 0000         005 7         36         2         10         8560           0 9 0000         005 7         36         2         10         8560           0 9 0000         005 7         36         2         10         3662           0 9 0000         005 7         36         2         10         3662           0 9 0000         005 7         36         2         10         3662           0 9 0000         005 7         36         2         10         3662           0 9 0000         005 7         36         2         10         3641           0 9 0000         005 7         36         2         10         3641           0 9 0000         007 7         36         2 <t< td=""><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>- 3</td><td></td><td></td><td>- 102</td><td>10</td><td></td><td></td><td></td></t<>								- 3			- 102	10			
0.9 0000         0.0 3         30         5         10         9500           0.9 40056         0.0 19         20         7         10         9500           0.9 40056         0.0 19         20         7         10         9500           0.9 40056         0.0 12         20         1         9540         9540           0.9 40056         0.0 12         20         1         9540         9540           0.9 40056         0.0 12         20         1         9540         9540           0.9 40056         0.0 12         30         2         10         9540           0.9 40056         0.0 14         30         2         10         9600           0.9 40056         0.0 14         30         2         10         9600           0.9 5         0.0 12         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         9600         10         10 <td>(DOAR)</td> <td></td> <td></td> <td></td> <td></td> <td>KHU11</td> <td>2001</td> <td>28</td> <td>1-04</td> <td>184642</td> <td>10.01</td> <td>TH</td> <td></td> <td></td> <td></td>	(DOAR)					KHU11	2001	28	1-04	184642	10.01	TH			
0.9000         0.053         36         9         17         856           0.94005         0.757         28         7         9         936           0.94005         0.757         28         7         9         936           0.94005         0.777         28         7         9         936           0.94005         0.777         28         7         9         936           0.94005         0.777         28         7         9         936           0.94005         0.777         28         7         9         936           0.94006         0.741         28         3         9         936         9         936							2064	- 28		10.542	-16.00	15			
P H 4000a         EVE 2         28         2         10         2         94         2         94         2         94         2         10         2         4         2         10         2         4         2         4         3	10001					1023		- 3	102	10.545	- 10	- 16			
P M 4005         EVE 7         300         27         91         3934           0.4 4005         DO11         200         2         1         3448           0.4 4005         DO11         200         2         1         3448           0.4 4005         DO11         200         2         10         3448           0.5 4000         DO14         400         2         10         3458           0.5 4000         DO17         100         2         10         3458           0.5 4000         DO17         100         2 <t< td=""><td>UTTH-</td><td></td><td></td><td></td><td></td><td>8797.5</td><td>210</td><td>- 21</td><td>187</td><td>10.000</td><td>100</td><td>10</td><td></td><td></td><td></td></t<>	UTTH-					8797.5	210	- 21	187	10.000	100	10			
P H MDe         Dot 7         HB         2         H3         H6         H6           0 4 MDe         DOT 5         H6         3         46         36         46						R18*1			N1		1004	2.8			
P 9 (MDe)         D 01         20         3         40         8000           P 9 (MDe)         D 014         20         51         0000           P 9 (MDe)         D 014         20         51         0000           P 9 (MDe)         D 014         20         51         0000           P 9 (MDe)         D 014         40         20         51         0000           P 9 (MDe)         D 014         40         20         61         00000         00000         00000 <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>3261</td> <td>28</td> <td></td> <td></td> <td>1044</td> <td>2.8</td> <td></td> <td></td> <td></td>							3261	28			1044	2.8			
D 9 (600e)         DD 9 (100e)         DD 9 (100e)         DD 9 (100e)         D 9								28			10.01	18			
0.9         0.9         0.9         4.0         3         4.1         84.00           0.9         0.00         0.0											1007	10			
0.9 (a)(b)         0.055         40         50         60         80								22			- 960	TE			
P14-0075         CDP14         407         7         844         2546           CD-40005         CDP15         SCD         7         86         25444           CD-40005         CDP15         SCD         7         86         25444           CD-40005         CDP15         SCD         7         86         25444           CD-40005         CDP15         SCD         7         86         2644           CD-40005         CDP15         SCD         7         86         2644           CD-40005         CDP15         SCD         7         86         26         9         3644           CD-4005         CDP15         SCD         7         86         3644         36								- 2			- 196	18			
M M 6000+         X0977         M00         X1         M0         X1444           M 6000+         X0977         M00         X1         M0         M044           M 6000+         X0977         M00         X1         M044         M044								1 2			- 162	10			
0.6 MDe 2017 808 20 19 2644 0.6 MDe 2017 968 20 19 2644 0.6 MDe 2017 968 20 19 2644											1764	2.9			
U 18 00De 10/07 1000 20 100 00 004								27			104	2.8			
1744 MIDer 20 111 38438								22			1954	2.8			
											1954	2.8			
1751 Faller 20 111 Brillion								2			9.0	11			
	THE R. L.					8/811	100	- 22		101	141	24			

This will return you to this screen:



To adjust the y-axis press the y-axis button and follow the same steps as on previous page. Once you have highlighted the cells that you want press return on the keyboard and then click **"Next >"**.

Fill in the correct Chart Title, X-axis and Y-axis titles then click **"Next >"**. To move the Legend (where it says what the series is) press the Legend tab at the top.

You must then decide whether you would like the graph to be produced within the original Spreadsheet or in a new sheet.

Chart Wizard - Step 3 of 4 - Ch	nart Options
Titles Aves Gridines Le	gend   Data Labels   Data Table
Chert title: Graph of Split (/900) against E	Graph of Split (7999) against Distance (Metree)
⊆ategory (X) axis: Distance (In)	• (94)
Splite (V) accie:	
Second cabegory (1) axis:	01205
Second value (V) avis:	4° 4° 4° 4° 4° 4° 4° 4° 4° 4° 4° 4° Marson (n)
	béci
	noal < gack gaot > Enanh

Selecting **"As a new sheet:"** is preferable as it means that you can access the graph and the data without having to scroll around the page or move the graph.


If you choose **"As new sheet:"** then you will need to enter the name that you want to appear on the tab at the bottom of the sheet.

Click "Finish" and your graph will be produced.

Charl Wizard - Step 4 of 4 - Charl Location							
Place charts -							
	C As new gheet:	Chart1	_				
	🌾 As gbject in:	Sheeti	•				
7	Cancel	< Badk Next >	Brish				


Your graph will be produced as opposite. To add a Trendline to the graph right click with the mouse on the line of the graph. This will show the box of options as shown above. Select **"Add Trendline..."** and then choose the type of Trendline you would like to add from the list.






Now that the graph has been created you can use it in other documents by selecting Edit, then Copy, from the top of the page, or pressing **'Ctrl + C'** then pasting the graph into another document like this:

It is also possible to create a graph with two sets of data with a different axis at each end e.g. Split/500m at one end and Heart Rate at the other. Such an example is shown below.



To create a graph like this you need to start the process as above but when you get the Chart Wizard you need to choose the Custom Type, **"Lines on 2 Axes"**.


Click "Next >" and select the Series Tab.



Add the first series as before then press "Add" and go through the same procedure as previously to add the second series. Press the button marked above as Series Data and select the series from the Spreadsheet. Then continue the process as before.

Once this is done you need to change the title of the Series so that you know which is which. To do this either type into the box marked above as Series Title, or press the button and select a cell containing the title from the original spreadsheet.

Try experimenting with different types of graph to see which displays your results the best.



#### 2.8. Downloading the Concept 2 Rowing Log

Open up the Internet Explorer (Start > Internet Explorer). Then type in the address:

#### www.concept2.com/05/rower/service/pm3software.asp

Scroll down to the Concept 2 Rowing Log then click on the highlighted Concept 2 Rowing Log. This then leads to a page like the one below:

From a page similar to the one below click on the highlighted **RowPro Demo Edition version 1.7 (Image 1)** This link then takes you to the download center at digital rowing, like the one below.



Click on either of Download Now buttons to download the **RowPro 1.8 Home Edition**. A box then appears where the installation file can be saved to an appropriate location. Click OK then the file will start downloading. After the file had been downloaded click Run to start the installation and follow the on screen set up instructions. The installation can also be completed at a later time by locating and double clicking the installation file to start the RowPro setup program. Once again follow the on screen instructions to complete the installation.

#### 2.9. Installing the Concept 2 Rowing Log from CD

Insert the CD titled **"PC software for your PM3"** that came with your PM3 or Model D. This will automatically open the Concept 2:PC Software Suite (if this does not open automatically go to the start menu, select my computer, select the CD drive). This should look like this:



Click on the Button next to C2 Logbook image. This will display the screen opposite:

Click **Next >** If a license agreement appears then read and accept it.



The Software will load by default into the Program Files folder on the C: drive. It will create a folder called Concept 2 if one does not already exist. If you would like to change the location of this program click change and select the folder where you would like it.

Ø Concep	12 Rowing Log - InstallShield Wizard
Destinati Click Neo	en Folder at ha install ha this folder, or clid. Change ha install to a different folder.
- 23	Install Concept2 Rowing Log to:
	Cil/hagran Riss(Concept2)(C2 Rowing Log), Change
Distalistield -	<back next=""> Cancel</back>

You will then be shown the following screen.

Click on **Install** and the program will install onto your computer.

i Concept 2 Rowing Log - InstallShield Wizard
Ready to Install the Program The vizard is ready to begin initialation.
${\rm F}$ you want to review or change any of your installation settings, click Back. Click Cancel to exit the vistand.
InstaliSheld Cancel Cancel

Once the Program has installed you will be shown this screen. Click **Finish** and you are ready to use the Concept 2 Rowing Log.


It is also possible to download the rowing log from the Concept2 website.

#### www.concept2.com/05/rower/service/pm3software.asp

🕫 Concept2 Rowing Log - InstallShield Wizard						
2	InstallShield Wizard Completed					
	The Installisheld Vistart has successfully installed Concept2 Rewing Log. Click Finish to exit the vistard.					
	< Back Finish Cancel					

#### 2.10. Using the Concept 2 Rowing Log

Using the USB cable that comes with the PM3, connect your computer to the MP3 Monitor. (The connection for the USB cable can be found at the bottom of the monitor).



Flywheel sensor cable must be connected here for the PM3 to operate. The Model D sensor will also supply power to the PM3 while you are rowing. The PM3 can be set to operate with either the Model D or Model C. They are not interchangable.

Port for the optional heart rate receiver.

USB Port for connecting to a personal computer. See www.concept2.com/pm3 for current information on PC functions.

Open the Concept 2 Rowing Log. (Start > All Programs > Concept2 > RowPro> Concept2 Logbook). This opens up an initial box like the one below:

To add a user click the  $\ensuremath{\textbf{Users}}$  button and add the name of the user as shown.

Filman	C X	сот	nepst 🖂 Loca	OOK .	Protokinsten Updiere OpeningBolonce:		actes
Date	Categos	Tige	Fornet	Fine Hones	al 1500 n   Wilphy	Ca Meon	
11.ugCer	d., h	npert	Hase all http:	. Print Log			Help

Governt? Legt	aok 1.803		×
Ellera	Ø User		8.
Láe C	Current Concept	2 Logbook users:	
	Chris	0 rows	A46
			Dolete
Usels.			Close

# Add new data from the PM3 LogCard

the box below should appear below:

To add new data from the PM3 LogCard click on the PM3 LogCard box. The window opposite will be displayed.

Click on Read LogCard. After the LogCard has been read

Concept2 Legisek 1.003

 FM3 Logiand Mility

 Feed
 Feed

Consecution Consecution (Consecution) El Phil CongConst (Lifflight	_	×
Reads		ReatLogCard
раз тако тура	Telo Midora	Selected
		Dependent 24
		debelog
		2qktr.
Status 📕 R42 LogCed loand		Cèse

To add data to the C2 Rowing Log select the required data and then click on the **Add to Log** box. After all the required data has been added click **Close**.

nooriilagia Hiilagiar					
Lines BES	1				First Locard
Oate	1 Pres	1 Spe	Tine	Moters	
1201000	18.15	CONTRACTOR	30:30	8,400 910	Tobol All
1397(3805	18:42	Just Row	1.25	696	Unselved All
					Adde ing
					3 skito
Stree	Pester	njeksi uumenlalji			Close

Films in	6.1	TO A REPORT OF THE PARTY OF THE					ionUs/Dein pHalanan	Du. Neten 🔽	mellera	
0-ekp	Categos	Type Castin	Femal	Time 2003.8	Hoter LAT	al.ecor.	V Upbe	Ex. Motore 1		

This will return to the main C2 Rowing Log with the information on it, which should look something like this:

#### Importing data to the C2 Rowing Log.

When at the initial C2 Rowing Log page (similar to that of the last picture and occurs after opening the C2 Rowing Log), click on the **Import Rowing** box. This will open a box like the one opposite.

Select the required data type either Import a RowPro RowFile, Import an eRow workout file or Restore a previous RowPro/Concept2 Logbook database. Note: The last option overwrites the current database.

Then click Import.

Click on the appropriate data, then click on open and this will then add the data to the C2 Rowing Log



Open				28
Look in:	Ny Documents	*	+ 国合田·	
Hy Decarrents Decktop My Decarrents Hy Computer	Ethic Concept2 My Mosc My Rose My Received File: RowedSheldth RowedSheldth RowedSheldth Scheols Scheols Sparaenthip Tharsday Plannig Meetings			
Ny Network Piaces	Fieratue		-	Dpen
	Files of type: Powelle ["sow]		-	Cancel

#### Adding data manually to the C2 Rowing Log

From the initial C2 Rowing Log page click on the manual entry box. This will then open up another page which should look similar to the page opposite:

Then the user should enter the data that they want to, manually into the appropriate boxes. Then click on the Add Split box. If any data is entered incorrectly and wants to be removed then click on Remove Split. Then to add the data to the initial C2 Rowing Log page click on add row. Once all the data has been added click on **Close** which will take the user back to the C2 Rowing Log page.



# To Print a Report

From the initial C2 Rowing Log page click on print report. This will then open up a page like the one opposite.

From this page then the report can be printed by clicking on the **Print Report** box or the page can be closed by clicking the **Close** box.

# **Reset View**

In the initial C2 Rowing Log page click on the **Reset View** box to put the view back to how it was.


## Help

If any help is needed then the user should click on the **Help** button which can be found on the initial C2 Rowing Log page. Here most problems encountered can be tackled.

# Generating a Report using the C2 rowing log

Using the USB cable that comes with the PM3, connect your computer to the PM3 Monitor.

(The connection for the USB cable can be found at the bottom of the monitor).



Flywheel sensor cable must be connected here for the PM3 to operate. The Model D sensor will also supply power to the PM3 while you are rowing. The PM3 can be set to operate with either the Model D or Model C. They are not interchangable.

USB Port for connecting to a personal computer. See www.concept2.com/pm3 for current information on PC functions.

Then insert the LogCard into the PM3 monitor.

Open the C2 Rowing Log. (Start menu > Programs > Concept2 > RowPro> Concept2 Logbook)

This will lead to a C2 Rowing Log without any information on it. To add the data to it, click on the PM3 LogCard. This then opens up a box with the recorded data in it. Click on the box beside the desired data and then click on **Add to Log**. Then to close box click on **Close**.

This will open up the C2 Rowing Log which will then look like this:

Files at	CI.	one	spt⊡⊥c	6400	к	lan Up/Dvi in Biolonos:	Ca. Metais P	meters
Late	Extremulation of the second se		Femal		100 800 01.0 2.0	MUpter 1/3	Du Histers 2042	

Conce	pt2 Logb	look							0	nele .
Filter the	Single: 011						W	um Upitho in 6	(u. 184	0010
Dep-	Category LogCard	7904	T1000	Meteral	Arg Pace	Colle 1954	Work	Con. Nobes	110	68
unt Pisce No. 1			14/54	- 10-1			Trans Re-	Aur. 1084		,

Highlight the data line required, then right click the highlighted area to see the options tab. Click on **Details** in the tab.

G Concept? Lagbook	1.803			
E Nes a	concept	LOGICOK	Include Water BorDavie Ca. Opening/Solence	Maas P Fineten
Date Catego 2009-1-20 LugDo	or Type Frend d Cardin Cove	Teen Plates Celate Celate Transfor Oladay + Indep	11 (1644)   WillyDes   1   1914   191	2.142
PKitegCast.	lepert. Have	dfirity	. Read You	Halp
Uses	Current User:	Chris Breti	•	Clocs


This then generates a report similar to the one opposite. The report can then be printed by clicking on the **Print** button or closed by clicking on the **Close** button.

RowPro Sess	ion Repo	ort		Aue	ni ky Owi		inacus Si 3 Gobeles	
2415	Time	Meters	Aug Pale	Avg DPS	Ang Notes	Cara	Are and	Esc HR
1	2336.0	481	2103	8.2	18.1	28	10	
1	3 (01.0	480	3111.4	8.2	788.0	28	28	
1	2.01.0	60	211.4	8.8	101.0	26	28	
4	2010	440	213.6	2.2	147.8	87	29	
4	106.0	208	2114	9.1	154.0	-14	28	
Fetale	8.01.0	2,842	2.11.2	8.6	191.4	483	25	
Sum Nam Sp/Dr.	8.05.6							
Overall	ROLE	LINE				10		

# 2.11 Deleting Files from the LogCard Using the Concept 2 Rowing Log

Using the Concept 2 Rowing Log is the only way of removing files from your LogCard.

Using the USB cable that comes with the PM3, connect your computer to the PM3 Monitor. (The connection for the USB cable can be found at the bottom of the monitor).



Flywheel sensor cable must be connected here for the PM3 to operate. The Model D sensor will also supply power to the PM3 while you are rowing. The PM3 can be set to operate with either the Model D or Model C. They are not interchangable.

USB Port for connecting to a personal computer. See www.concept2.com/pm3 for current information on PC functions.

·

Open the C2 Rowing Log. (Start> All Programs> Concept2> RowPro> Concept2 Logbook)

This opens up an initial box like the one opposite:

Filters an	C COM	COCROOK	Include Virlam Up/Din in I Episeting Bullance	
0.80	Emigray Fyrm	Fores Time 5	aan Wikter ( trigte	Eu Henes

To add new data from the PM3 LogCard click on the **PM3** LogCard box. The following screen will appear:

Click on **Read LogCard**. After the LogCard has been read the box below will appear:

User		<u>+</u>		
Pero				Final option
Oate	Ine	Type	Fine Madex	
				Calver 48
				India: Al
				Attalia
				Deleter
Status:		Collord		=

Highlight the workout that you would like to delete, then click Delete. This will remove the workout from the LogCard.

Warning: Please be advised this action is irreversible.

Line Rist					
Non-Ro	_	1.			Final LogEn
Date 11/01 (2004)	104	Tope Contrained	Tene 10.00	546412 0,023	Select 43
150(2005	他将 第42	Just Row Just Row	1.85 2.21	6,85 152 978	Unedect.A
					Add to Log
					Delate

# The Personal Training Log

### 3.1. The Personal Training Log

The Personal Training Log, can be found at http://www.concept2.com/sranking03/

Here you can either log in or, if you are a first time visitor, register. Registration is a simple, free process that should take no longer than a couple of minutes.



## 3.2. Current Season


After you have logged in, you will see the **"Current Season"** page.

From here, the user can update their training and add any recent workouts. This is done in the **"Add New Workout"** box, filling in the appropriate information and then clicking **"Add"**.

Underneath the **"Add New Workout"** box all the information for the current season can be seen. There is also the option to edit and delete the information in the right column.

Below the current season information there are notes to remind the user about certain specifications such as the qualifying rank categories, the work out definition and weight classes.

The user can then change to different sections within the personal training log by clicking upon different categories on the top bar.



#### 3.3. History

Here season summaries, lifetime totals, and archived results can be seen. By clicking on the archived results, all workout pieces logged in each year will appear. There is also the option to edit or delete the information, by clicking on the furthest right columns.

	11/1/2			MPLOS I MARING	2	
Gummt Season	History	Unaffertation	Ganked Merkouks	Enolite	loss	Lopez
		ranan Gamma iyi	erap erirelite ber			
		115 mind on Carner ary	4,278	01.045		
				82,000		
		relate fatali	0.0	71.542		
		<ul> <li>2005 Olar 5.0</li> </ul>	044eni 38, 90850 関 16	- lines		
		* 2004 (Nor 1.9 * 2002 (Nor 1.9	20-404 31, 2084 11 10 10 10 10 10 10 10 10 10 10 10 10	niligeri niligeri		
	_	ing	Hindury Selec	_		
	Hadronical man	fors are estomatical	r selectated each year at t	to and of the		
	wars in such	binkerizal-serier reco	ni, or said arrans markhly i or to the carrent "tree" sig	initial hav aren notar -		

#### 3.4. Challenges

Here users can see how they are ranked on the Annual Metres Honour Board, which shows participants the average daily metres rowed for all ranked participants. The user can also see where clubs and universities stand, and see forthcoming challenges and events.


Further down this page there is a **"Weekly Winners"** section; the **"Million Metre Club"**; and ranking statistics, where information about the overall log is displayed. The **"Million Metre Club"** gives out prizes for people who achieve certain distance targets, for example one million metres.



#### 3.5. Ranked Workouts

Within the **"Ranked Workouts"** the user is able to quickly see how their times and distances compare to others. The view initially opens with the current year on show but by clicking on previous seasons, the user is able to see where they have been ranked previously.

For more on this side of things, see "Rankings" below.




## 3.6. Profile

Within the Profile area the user is able to view and edit their profile, and add any additional training partners. Underneath the Profile Settings, there is a small **"Edit Profile"** button. They can change any information and then either accept it by clicking agree, or rejecting it by clicking reject.



## 3.7. Teams

Within the **"Teams"** section, the user can see results from team events and view where their team stands within the standings. You can also manage the team as well as create new team events.



#### 3.8 Rankings

By clicking on **"Rankings"** at the top, you can see all the Ranked pieces from everybody who has signed up for the Personal Logbook. You can view these without having registered for the Personal Logbook yourself. There are various ranking distances, ranging from 500m to a full marathon (42,195m). You can either view the best times for the entire ranking, or you can search by criteria such as gender, age, weight and country.

#### 3.9 Log out

You should logout of the Personal Training Log when you are finished using it.



# Venue Racing


## 4.1. Downloading the Venue Racing Software

Open up the internet explorer (start > internet explorer). Then type in the address

#### www.concept2.com/05/rower/service/pm3software.asp

Scroll down to the Venue Racing Software then click on the highlighted PM3 Venue Racing Application. This then leads to the next page like the one opposite:

Then click on the **Save** or **Run** box, accept and click ok. Then the software will be downloaded and then can be used.



A download dialogue box will now open giving the options Run, Save or Cancel.

To install immediately click **Run**. When the download is complete click **Run** to start the installation. This will open the Installation Wizard as shown in section 4.2. Follow the instructions in 4.2. to complete the installation.

To install at a later time click **Save** and select a download location for the installation file. Once the file has been downloaded the software can be installed at any time by navigating to the download location and double clicking on the installation file. As above this will open the Installation Wizard. Follow the instructions in 4.2. to complete the installation.

### 4.2. Installing the Venue Racing Software

Double click on the appropriate downloaded setup, The Installation Wizard will pass it through some set up pages before coming to the page opposite:

Click on **next** button:



This then leads on to the next page which should look similar to the window opposite:

Accept the terms of the agreement, then click **next**, which should the proceed onto the next page.



No PM3 Venue Race Application - InstallShield Wizard	×
Customer Information Please enter your information.	C2
Ljow Narae	
Qrganisation:	
Install this application for:	
Anyone who uses this computer (all users)	
O Only for we ()	
InstallShicki -	
< Back. Piest >	Cancel

Fill in the appropriate information, and then click Next.

This should lead to the page opposite. If the destination to install the Venue Race application is okay, then click **next**, but if the destination is not the desired one then click **change** and set the appropriate destination. Then click **next**.

(PM3 Ve	nue Race Application - InstallShield Wizard	×
Cherter and	ion Folder cit to install to this folder, or dick Change to install to a different folder.	C
	Instal PM3 Venue Race Application to: C: (Program Piles),Concept2/Venue Race Application),	Change
traditivek) -	< Back Next >	Cancel

Chose the appropriate setup type and then click  $\ensuremath{\textit{next}}.$ 



The box opposite then appears confirming the installation information. If this information is okay then click **Install**, but if this information is wrong then go back and change it.

The installation then occurs and then when the installation finishes click **finish** to close the installation box.

PM7 Venue Race Application - InstallShield Wizard	1
Ready to Install the Program The vision is ready to begin installation.	Cz
If you want to review or change any of your installation settings, clid. Back, i solithe waterd. Current Settings	Click Cancel to
Setup Type: Wineless and USB Racing	
Destination Polder: CIIProgram Resi,Concept2(Venue Race Application)	
User Information Name: Company:	
stal5hald	
< Back Instal	Cancel

## 4.3. Using the Race Venue Software

Prior to running a race, you must decide on which method to use to connect the PM3s to the Venue Race Application. This is often decided by the size of the venue. The following table can be used to determine the method of connection that will best suit your race. For most systems in schools it will be appropriate to use the USB system as there will not be enough machines being used to warranty using any of the other systems.

### **Connection method guidelines**

CONNECTION METHOD	RECOMMENDED VENUE SIZE	MAXIMUM RESTRICTIONS	REQUIREMENTS
USB	2-20	Maximum 28	Hubs
Wired	10-40	Not tested over 40 units as of 1/22/05	Wired modules
Wireless *	20-60	Tested up to 56 units	Wireless modules

## Installing the Venue Race Application (VRA)

Before racing, your PC meets all minimum requirements and make sure that all PC power management features such as screen savers are turned off.

Download the latest version of the Venue Race Application and associated utilities from:

## www.concept2.com/products/pm3/venue.asp

Run the setup.exe file you downloaded.

Click I agree and then click **Next**.

Continue clicking **Next** until the installation is complete.

Take note of the new icons on your desktop, as well as the new options in your Start All Programs menu. The icons on your desktop are as follows:

- PM3 Venue Race: This is the Venue Racing program. It is similar to eRow but for the PM3.
- PM3 Venue Race DHCP Server (TFTP): This icon is only for WIRELESS 802.11 racing with wireless adapters (PN 1984). You can delete this icon if you are using USB racing (or you choose to install only the USB version of Venue Race Application and utilities).
- PM3 Firmware Update for Venue Racing: This icon is for updating the firmware in the PM3 for USB or Wired racing.
- PM3 Expansion Firmware Update for Venue Racing: This icon is for updating the firmware in the expansion hats.
- PM3 Firmware Restore to V82: This icon is for restoring the PM3s to version 82 following the race.
- Start then All Programs, and then Concept2: This contains several menu options, including restoring PM3s to Version 82 firmware following the race.

## 4.4. Use in Schools

For most systems in schools it will be appropriate to use the USB system as there will not be enough machines being used to warranty using any of the other systems.

For connecting the machines together download the support documentation from the Concept 2 web-site (see section 4.12) and read the usblayout.pdf document.

To access the race venue software click Start, Programs, Concept 2 and then double click on Race Venue Software.

The page opposite then opens up, click on **Next** which then proceeds to the following page:



Here select the appropriate interface options, which will usually be USB, and then click on **Next**. A similar page should then appear:

Erg Communications	×
Indoor Racing Setup Wizard Step 1: Select Connection Method	D)
Please select how the Ergs are o then press Next.	onnected to the computer,
Interface	
Ø US8	
C Wired with RS485Expension Modules IP Subnat C Wineless [192:169:1.0	IP Address (1-250) Stat End 1 40
	< Back Next> Cancel

The computer will then discover the Indoor Rowing Machines (Ergs). Please make sure that the monitors are on when discovering the machines on the race system. If the right amount of Ergs in found, click **Next**. But if this number is wrong then click **Help** and rediscover. Keep discovering until the right amount of indoor rowing machines is found by the race venue software. Once they are discovered click **Next**. Then a similar page should appear.

rg Discovery			Þ
Indeer Racing Setup Wisard Step 2- Erg Discovery			Ľ2
The computer has found 2 If this is correct, press Nev If this is not correct, press	d.	ce.	
Help			

Then click **Number all Ergs**, and then go to all of the monitors and press the next lane button. Use the accept or reject lane options to assign the appropriate lane numbers to the Ergs.

After accepting these lane numbers click the **Done Numbering** button which appears on the screen. And then click **Next**.

This will then take you on to the following page:

Erg Numbering	X
Indeor Racing Setup Wizard Step 3: Seting the Eig Numbers	3
One or more Ergs has not been numbered. Please press "Renumber all Ergs".	
The computer is communicating with 2 Ergs, numbered:	
Number all Ergr	
Carter (Back (Next) Carter	noel

Then select the appropriate options, in stages 1,2 and 3, then click  $\ensuremath{\text{Next.}}$ 

inter the race type, grouping lext.	g, and heat name, then press	
I. Enter the sace distance or time->	Citiance 2000 Mater:     C Tine 0:05:00 Materia	
2 Race az->	Singles     Doublex     Fours     Eighte	
<ol> <li>Enter the heat name &gt;</li> <li>This will be displayed on the PM3 duit</li> </ol>	Unifiled ing race warmup	

Then fill in the participants name into the appropriate box. Click **Next** which should lead on to a page similar to the page opposite:

			_
	number of boats and the n	ames i desirec	i,
hen pres	S NEI.		
Nunber	ol boalo inirace 🧇 🕕		
		_	
	Participant Name		3
1			
2		_	
3			
4			
5			
6		_	
7			
8			•

Then click **Finish** and the follow box should appear:



Here the race data can be saved by changing the file name and/or changing the desired location, and then clicking **Save**.

Then the program is set up and all that remains to be done is click on the **Prepare to Race** button in the PM3 Indoor Racing Control Panel. The screens will then count down and the race will begin:

Open	? X
Look in: 📋 Recent	• E ff ∰•
File name:	Open
Files of type:	v Cancel

## 4.5. How to set up a New Race the Race Venue System Software

PM3 In	door Ra	acing Con	troi Panei		Done /	\ddres	ssing 1	Ergs		Г	More Status
· · · · · ·	<u> </u>	1	1	-		e Display S	Scale			1	1
New	Open	Modily.	Prepare to Race	100M	200M	500M	1008M	Auto	Setup	Options	Heb

On the above panel click on the **New** button. This will then take you on to the following page:

Then select the appropriate options and click Next.

Enter the race type, groupin Next.	g, and heat name, then press	
1. Enter the sace distance or time $\rightarrow$	Distance 2000 Materia     Taxa 0.05.00 Microso	
2. Receiver->	<ul> <li>Findes</li> <li>Doubles</li> <li>Fours</li> <li>Eights</li> </ul>	
3. Enter the beat same > This will be displayed an the PM3 du	U withed ing race warmup	

Then fill in the participants name into the appropriate box. Click **Next** which should lead on to a page similar to the window shown on the next page.

Rawer Setup		×
	cing Setup Witzerd Enter Perioipent Namer	
then pres	number of boats and the names i is Next. Infoatsings > 11	í desired.
	Participant Name	-
1		
2		
3		
4		
5		
6		
7		
8		
	( Bosh	New) Cancel



Then click **Finish** and the following bow should appear:

Here the data can be saved by setting the desired file location, changing the file name and then clicking **Save**.

Then the program is set up and all that remains to be done is click on the **Prepare to Race** in the PM3 Indoor Racing Control Panel. The screens will then count down and the race will begin.

Serve in: 🖸	) Flaces	• ⊨ © ₫•
File name:	Untilled	Sava

## 4.6 Opening Saved Races



Inside the PM3 Indoor Racing Control Panel shown above, click upon **Open**. This following box will pop up.

From this box, **Modify Race**, the data can be changed from the original data which was saved. Once the information has been altered click on **Ok**. Then the program is set up and all that remains to be done is click on the **Prepare to Race** in the PM3 Indoor Racing Control Panel. The screens will then count down and the race will begin.

Mod	ify Race			
Rø	os Nane:	United		DK.
.0	Distance	2000	Matara Grouping: Singles •	Canoal
C	Tine	0:05:00	hitematese 🔲 Sava Stroka Data	
Sta	rting Eig N	unber: [1		Splits
	Partic ipant	Count	Birthdate (mm/dd/yyyy)	1
1	Lone1	-		
ż	Lone 2	-		
3		-		
4		-		
5		-		
6		-		
7		-		
8		-		
.9		-		
10		-		
11		-		
1				•

## 4.7. How to Change the Race Setup

PM3 In	door Ra	icing Con	trol Panel				sing 1	Ergs		- F	More Status
New	Opan	Modily	Propare to Race	100M	200M	e Display: 500M	1000M	Auto	Setup	Options	Halo

On the PM3 Indoor Racing Control Panel, shown above, click on the **Setup** button. Then the following picture should appear. Here the way the rowing machines communicate to each other can be altered and new machines can be discovered if they are lost.

By clicking on the **Erg Numbering** tab the machines numbers can now be altered.

etup	
Please sele	ns [EigNunbeing] ct how the Eigs are connected to the computer, Discover to find the Eigs.
Interface	
@ USB	
C Wretewith	IP Addexce (1-250) IP Subret Start End 192-168-1.0 1 40 Changer WIR Dania
Discover	Ergs Communicating 2
	DK Cancel Apply

Once the appropriate ergs have been renumbered or the communication has been altered then click **Ok** so the settings can be used in the race setup.

Setup 🗙
ExpCommunications Erg Numbering
Press one of the buttons below to number the ergs.
The computer is communicating with 2 Ergs, numbered 1-2
Starting Physical Address 1
Number all Ergs
Computer auto number all Ergs
DK. Cancel 40019

## 4.8. How to Change Race Options

PM3 In	door Ra	icing Con	Done Addressing 1 Ergs							More Status	
New	Opan	Modily	Properts to Race	100M	200M	e Displays 500M	Scale 1000M	Auto	Setup	Options	Help

By clicking the Options box in the above PM3 Indoor Racing Control Panel, the following box appears below.

By clicking on the **Preference** tab a screen similar to the one above should appear. In the **Paths** section of this box the files the race data, the race results and split/stroke data can be easily changed by typing in the desired location. In this options box the start type can also be altered to that desired by clicking on either **Countdown**, **Random** or **Modified Random**. Report types can also be altered in the **Options Preferences**. Then if the **Race View Options** tab is clicked the following view should appear:

tions	
Preferences Receiver Options	
Paths Recei: EUTIMATERCOMPANYConceptedUcence Race Results: C:\Documents and Settings\ffon\VER	(ONT \Ny Da
Split/Stroke Date: CNDocuments and Settings/Ton/VER	MONE VMy Do
Start Type Countdown Rendom ModifiedRandom	
Reports © Generate comma delinited reports. © Generate tab definited reports.	
DK Cancel	Apoly

Here the view of the race can be altered easily by clicking and ticking the appropriate boxes. Once the appropriate changes have been made then **Ok** can be clicked and the view will return to the race screen.

ptions Preferences Race View Options	
Right Column G Show Average Pace	
C Show Durient Pace Show Projected Finish Time/Meter	
Sort lanez every 100 Meters.	
Always display lower names.	
🔽 AutoSicale is default.	
DK. Cancel	Apply

## 4.9. Showing More Race Information

PM3 In	PM3 Indoor Racing Control Panel Done Addressing 2 Ergs									More Status	
						1 1	1				
New	Open	Madify	Prepare to Race	100M	200M	500M	1000M	Auto	Setup	Options	Help

Within the PM3 Indoor Racing Control Panel, if the **More Status** box is clicked then the following box appears which shows more information. If the data has been changed then click **Refresh** to get the updated sheet.

To close the Erg Status box click on the  $\ensuremath{\textbf{Close}}$  box.


					E	Clea	38	Batech					
.og#	Phys#	Port	Config	Qual	Level	Bat	Packets	Errors	SyncErr	Retries	Failures	Ор Туре	Race Stat
0	0	0	0		0	100			0	0	0	Phys Adr Init	Inactive
1	0	1	0	0	D	100	30.45		0	0	0	Phys Adr Init	Inactive
Z							2				1		
3													
4													
5													
6													
7													
8													
9													
10							2				1		
11													
12													
13													
14													

## 4.10. Changing the Race Display Scale

PM3 in	PM3 Indoor Racing Control Panel Done Addressing 2 Ergs										More Status
		1	Race Display Scale								
New	Open	Madify	Prepare to Race	100M	200M	500M	1000M	Auto	Setup	Options	Help

To change the scale of the race screen either click upon the race display scale on the following box:

Or the race display scale can also be changed by clicking on the **100**, **200**, **500**, **1000** or **Auto** and the scale will change appropriately:



## 4.11. How to Get Help

To gain help in the Race Venue Software click on **Help** on the top bar of the software shown below, or click on **Help** with in the PM3 Indoor Racing Control Panel.




## 4.12. Downloading Support Documentation for PM3 Venue Racing

Access Internet Explorer (Start > Internet Explorer). Then type in

#### http://www.concept2.com/05/rower/service/venue.asp

Then scroll down to the **support/documentation** section. The section should appear similar to this page opposite:

Then click upon the desired information that is wanted, and accept and save the information into a desired file.



# Updating the Software on the PM3


## 5.1 Downloading the Firmware Updater

Open up the internet explorer (start > internet explorer). Then type in the address


## www.concept2.com/05/rower/service/pm3software.asp

Scroll down to the Firmware Updater then click on the highlighted **Firmware Updater**. This then leads to the next page like the one opposite:

Accept the license agreement, which will lead the user onto the next page:



Then click on the **Run** or **Save** box, accept and click **OK**. Then the software will be downloaded and then can be used.



# 5.2 Installing the Firmware Updater

Double click on the appropriate downloaded setup, and then something similar to the following box will appear.

This information comes up on the screen. Click  ${\bf OK}$  to continue. The page then proceeds onto a page similar to the one below:

CARGE PARTIES.	3 Update Utility
System Locale	and a second
To use the sta	ity, you must have the heltening available to your
*PC-Corputit	is spärled screater with your reveal, as swellable from a comparise stored) is computer running Windows Hil, Selas, Ma. 2000, 39 Proc. or 30 Home. ney sath seed your vehiclosed operating hydrais cto.
Di valu motorri remingi@conce	er problems with the apolata, please context Commp42 et 3-800-249-5676 at 3-802-589-7971 at via emails pl2-com.
	OK Carol


Work through the steps one, two and three shown on the page and then press **Continue** to begin the firmware update process.

Once this process has happened, click  $\ensuremath{\textbf{OK}}$  on the finish box which pops up.

	are in your Concept2 Performance his update follow the steps below
Step 1. Connect your PN3 to a Step 2. Wait for Windows® to n (Choose "Next" if promp Step 3. Choose "Continue" to b	ecognize the new USB device. ted during device installation.)
Continue	Cancel

## 5.3. Using the Firmware Software

Using the USB cable that comes with the PM3, connect your computer to the MP3 Monitor. (The connection for the USB cable can be found at the bottom of the monitor).



Flywheel sensor cable must be connected here for the PM3 to operate. The Model D sensor will also supply power to the PM3 while you are rowing. The PM3 can be set to operate with either the Model D or Model C. They are not interchangable.

Port for the optional heart rate receiver.

USB Port for connecting to a personal computer. See www.concept2.com/pm3 for current information on PC functions.

On www.Concept2.com, there is the option of either downloading two types of firmware from the Concept site, Firmware or Beta Firmware. The Firmware updater will install the most up to date version of the software on to the PC to update the PM3 monitor found on the Indoor Rower. The Beta PM3 Firmware Updater will install the most current Beta Firmware software into your PM3 This updater contains Beta software intended to test new features or bug fixes and is not intended as permanent software for your PM3. By downloading and using this software you acknowledge the following:

- 1. This software may not fix any problems you are experiencing.
- 2. This software may cause new problems to occur including but not limited to data loss or loss of use of your PM3.
- 3. This software has undergone only limited testing and may not operate correctly.

Concept2 requests your feedback on all changes you discover we want to know about the good new features such as bugs fixed, new bugs and if the screens do not seem to format correctly. Please email comments to PM3@concept2.com

To update the software just download the program and then run it with the PM3 connected to a PC. The cable connects from the USB port in the monitor to the USB port in the PC. Concept 2 often release new updates of the software which is available from www.concept2.com.



VERMONT HOUSE, NOTTINGHAM SOUTH & WILFORD INDUSTRIAL ESTATE, RUDDINGTON LANE, NOTTINGHAM, NG11 7H0 TEL : 0115 945 5522 • E-MAIL : INFO@CONCEPT2.CO.UK • WWW.CONCEPT2.CO.UK